

GENERAL INFORMATION

The Morley Rock'n Verb is one of the finest devices in its class. A few moments of reading this pamphlet will provide a much shorter "getting familiar" period. The RNV may be used with any amplified instrument or microphone with normal range of impedance. Always use good quality shielded cable to minimize interference, noise, or hum. The RNV may be used with two 9 volt alkaline batteries or an external AC (mains) adapter.

OPERATING INSTRUCTIONS

Connect the instrument or microphone to the input jack, and the output jack to the amplifier. Be sure your A.C. adapter or batteries are installed. Set the four user controls to 12 o'clock. Push the foot switch to the position that lights the "effects on" indicator lamp. You should now be producing fine reverberation. The controls are marked and a few moments of experiment with them will help determine what best suits your needs.

1 - The Sustain Control

It adjusts reverberation time with full control of its duration from zero to 8 seconds, and anything in between. At minimum setting, an excellent doubling effect is obtained.

2 - The "Loudness" Control

The reverberation volume can be set from zero to louder than the original sound, with no acoustical oscillation, as happens with springs. Sustain time is unaffected by loudness.

3 - The Tone Control

The reverberation color can be set from warm bass to crisp highs. The direct signal is unaffected by the tone control.

4 - The Drive Control

Finally, something to really bend your ear - overdriven reverb. Turn the drive and loudness control fully clockwise. Turn the tone control fully counter clockwise, the sustain control to 12 o'clock. You now have a different kind of distortion. Don't hesitate experimenting with those controls. Try extending or shortening the sustain time - or reducing the drive. There are sounds there for you and your style of music.

The RNV can operate from two 9 volt batteries or the Morley A.C. adapter. The adapter is by far the most economical. If battery operation is more convenient, the alkaline batteries, despite their higher initial cost, are more economical compared to the cheaper zinc carbon 9 volters.

The unit is turned on when a cord is plugged into the input jack. The batteries are automatically disconnected when the A.C. adapter is connected.

WARRANTY

MORLEY BUILDS STATE OF THE ART PRODUCTS TO THE HIGHEST PROFESSIONAL STANDARDS OF QUALITY. THEREFORE, FOR ONE YEAR FROM THE DATE OF PURCHASE, MORLEY WARRANTS ITS PRODUCTS TO BE FREE FROM DEFECT TO THE ORIGINAL CONSUMER PURCHASER PROVIDED:

1. THE PRODUCT HAS NOT BEEN DAMAGED OR ABUSED.
2. THE PRODUCT HAS NOT BEEN ALTERED OR REPAIRED BY THE CUSTOMER OR AN UNAUTHORIZED SERVICE CENTER.
3. THE SERIAL NUMBER HAS NOT BEEN ALTERED OR ERASED.
4. THE GUARANTEE CARD IS FILLED OUT AND RETURNED TO US WITHIN 10 DAYS FROM DATE OF PURCHASE.
5. THE PURCHASER RETURNS THE PRODUCT TO US FREIGHT PREPAID IN THE EVENT SERVICE IS REQUIRED.
6. DEAD BATTERIES CAN LEAK DAMAGING FLUIDS WHEN ALLOWED TO REMAIN IN UNITS. MORLEY CANNOT WARRANTY DEVICES DAMAGED IN THIS MANNER. WE SUGGEST REMOVING BATTERIES IF EQUIPMENT IS TO BE STORED FOR LONG PERIODS.

ONCE THE ABOVE CONDITIONS ARE MET MORLEY WILL REPAIR OR REPLACE THE PRODUCT WITHOUT CHARGE TO THE PURCHASER FOR THE ONE YEAR GUARANTEE PERIOD.

M O R L E Y

A Division of TEL RAY Electronics Mfg. Co., Inc.